## Tea/Coffee Brewer Shut-down Procedure



## SHUT DOWN INSTRUCTIONS FOR BUNN TEA/COFFEE BREWERS

- Disconnect power
- Perform regular sanitation procedures

## CLEAN AND SANITIZE YOUR ICED TEA BREWER

1. Remove and thoroughly clean the entire brew funnel. The funnel tip and screen must be free from any tea particles or residue. Reassemble the funnel.


2. Remove and thoroughly rinse the spray head. The holes must be open and clear of any mineral deposits. Wipe the spray head panel clean with a damp cloth. NOTE – Any buildup on the spray head may restrict water flow and impact your brewing. For consistently great tea and coffee, clean spray head weekly with spray head cleaning tool. Upon visual inspection it may appear that light passes through all holes in the spray head, but a thin film of residue can pass light and still impede water flow.

- a. Remove spray head from brewer.
- Use the pointed end of spray head cleaning tool to remove any mineral deposits from the spray head holes.
- c. c. Insert the long end of spray head cleaning tool into the spray head fitting and rotate several times to remove any mineral deposits from the fitting.

3. The use of a damp cloth rinsed in any mild, nonabrasive, liquid detergent is recommended for cleaning all surfaces on Bunn-O-Matic equipment. Do NOT clean this equipment with a water jet device.

If you have any questions or problems, please feel free to call Coca-Cola at 800-241-COKE (2653) and ask to speak with myCoketech, who will be happy to assist.

## myCoketech





Spray head # 121049